



40 Dale St. West Babylon, NY 11704
Ph: 631-753-9550 Fx: 631-753-9560
www.unionconnector.com
www.companyswitch.com

Product Bulletin No.: PBF-601

Outdoor Enclosures for Company Switches

Features

- UL Listed NEMA 3R outer enclosure
- Galvanized steel construction
- Company switch is completely enclosed inside the NEMA 3R enclosure
- Lockable trapdoor on bottom for cable access
- Protection from weather and vandalism
- Units available to accept ALL company switches manufactured by Union Connector
- Powder coated for long lasting finish
- Company Switch is factory installed inside NEMA 3R

Options

- NEMA 4X outer enclosure
- Stainless steel construction
- Dual doors
- Recessed mount design
- Floor / Pad mounting
- Special labeling
- Custom color / finish



*NEMA 3R enclosure containing a 400A. Company Switch outside the Orange County Convention Center in Orlando, FL.
The 400A. Company Switch is completely enclosed and protected from weather and vandalism. The cable entry trapdoor on the bottom of the enclosure is closed and locked*



40 Dale St. West Babylon, NY 11704
 Ph: 631-753-9550 Fx: 631-753-9560
 www.unionconnector.com
 www.companyswitch.com

**Outdoor Enclosures
 for Company Switches**

Specifications

1. Enclosure shall be a UL Listed NEMA 3R, fabricated of galvanized steel .
2. Finish shall be ASA 61 Gray powder coat.
3. The enclosure shall contain (4) mounting tabs for surface mounting.
4. Dimensions for standard units shall be sized to accept standard Union Connector company switches as indicated:

Company Switch Type	Ampacity	NEMA 3R		
		Height	Width	Depth
CSC	60-100	36	24	10
CSC	200-400	42	24	10
CSC/SP	60-100	48	30	12
CSC/SP	200-400	54	30	14
CSC/SP	600	54	30	12
PBS/SP	60-200	48	30	12
PBS/SP	400	64	34	14

5. A drip shield shall be provided above the door opening.
6. The enclosure shall have a hinged front door and a handle able to accept a padlock.
7. The bottom of the enclosure shall contain a hinged trapdoor for entry of portable cable. The trapdoor shall be secured by a latch accessible only from inside the enclosure.
8. The Company Switch shall be factory installed inside the NEMA 3R enclosure.

