

Outdoor Company Switch

200A., 120/208V., Series 16 SafeCam[®] and Connection Chamber



- Electric power distribution center for theatre, convention centers, arenas, schools, churches, and events centers
- Series 16 SafeCam[®] receptacles
- 200A. Main breaker rated 65K AIC containing an integral shunt trip
- SafeCam[®] system monitors receptacles and activates shunt trip whenever a plug is disconnected from a receptacle
- Connection chamber for bare-end cables. Door is electrically interlocked with main breaker shunt trip
- Outdoor rated Type 3R enclosure
- Options:
 - ✧ Reverse Neutral/Ground
 - ✧ Parallel sets of receptacles
 - ✧ Isolated Ground
 - ✧ 1Ø - 120V., 120/240V.,
 - ✧ 3Ø - 277/480V., 208V., 480V.
 - ✧ Digital Meter
 - ✧ Custom color finish
 - ✧ Recessed or Pad mounting
 - ✧ Type 4 or 4X enclosure

Catalog Number: CSC-2010-SCSP-3R

Product Type: Company Switch with Series 16 SafeCam[®] receptacles and connection chamber

Main Enclosure: TYPE 3R, Galvanized Steel, ANSI 61 Gray powder-coat finish, wall mounting brackets, door for portable cable on bottom of enclosure

Dimensions: 40"H. x 24"W. x 10" D.

Rating: 200A., 120/208V., 3Ø, 4W+G

Circuit Breakers: Molded-case, UL489, 65K AIC @ 240V., (1) 200A., 3-pole

Receptacles: (5) Series 16 SafeCam[®] panel mount color coded receptacles with snap-back protective covers.

Busbar Output: (5) dual rated mechanical lugs on copper bus accessible in connection chamber

Monitoring: LED Indicator lights to indicate presence of phase voltage.

Labelling: Laser engraved cam identifiers and panel rating. Cable connection warning label per NEC Art 520.

Listing: UL Listed

Union Connector Co., Inc.
Jacksonville, FL 32256
631-753-9550

